



### DP2 SuperPole™

#### INSTRUCTIONS FOR INSTALLATION AND USE

1. Attach dipole center mount to secure mast pipe with U-bolts provided.
2. Attach the antenna elements to each side of the mount, hand tighten only.
3. Configure each side element of the antenna as shown in the drawings on reverse for desired frequency range.
4. Swivel the dipole mount to the desired angle.
5. Attach a 50 ohm coaxial cable with connector (PL-259) from the radio to the mount connector.
6. Set radio to desired frequency.
7. Fully extend telescopic whips to maximum length.
8. Adjust the SuperSlider for maximum receive noise gain at your desired frequency.
9. Check SWR. If needed, re-adjust the SuperSlider or slightly change the length of the telescopic whip as needed to obtain a low SWR below 1.5:1
10. The antenna is now ready for use.

### SUPER SLIDER™

#### ADJUSTMENT

1. LOOSEN KNOB SLIGHTLY
2. SET RADIO TO DESIRED FREQUENCY
3. MOVE SLIDER POSITION UP OR DOWN
4. ADJUST FOR MAXIMUM RECEIVE GAIN
5. CHECK SWR
6. FINE ADJUST: TELESCOPIC WHIP LENGTH
7. TO LOCK SLIDER: TIGHTEN KNOB GENTLY

### DP2 SuperPole™ Portable Dipole Antenna Deluxe INSTRUCTION SHEET



NEWSUPERANTENNA.COM  
 CUSTOMER SUPPORT  
 SUPERANTENNA CORPORATION  
 212 MARINER CIRCLE  
 LINCOLN CA 95648 USA

TEL: 1 - 916 - 434 - 9225  
 FAX: 1 - 916 - 645 - 1586  
 EMAIL: [antenna@newsuperantenna.com](mailto:antenna@newsuperantenna.com)