

SP-767

EXTERNAL SPEAKER

The SP-767 is a high fidelity audio transducer incorporating manual frequency tailoring specifically intended for amateur and general communications modes, as well as for broadcast listening, including wideband functions for music and FM reception. Independently adjustable low-cut and high-cut filters offer twelve possible audio response configurations select able from the front panel, enabling the operator to mach the audio to his ear under all conditions and modes. Two separate inputs are possible, which can then be selected by a front panel switch. Output for headphones is also provided on the front panel, so that the frequency tailoring capability of the SP-767 may also be used with separate headphones.

Filter Operation

The low-cut filter selector includes two filter positions in addition to the "NORM" position, while the high-cut filter selector includes three, plus "NORM" . The response graph on front panel indicates which combination of positions to use for each mode being received.

AM,FM These wideband modes usually call for maximum audio bandwidth and maximum fidelity. Set both filter selectors to NORM. However, should very low or very high frequency interference appear due to nearby stations, manmade or atmospheric noise, adjust the filter selectors accordingly to maintain pleasant reception.

SSB For the most natural sounding reception of these signals set the LOW selector to the NORM position, and the HIGH selector to position 1. Again, under crowded band conditions or high noise levels it will be advantageous to reset these controls for best overall reception.

CW In this narrow mode the LOW selector should be set to position 2 and the HIGH selector to position 3, resulting in a narrow audio response centered around 600 to 700 Hz. This filter characteristic is useful for CW reception with receivers that do not include narrow filters in their IF circuits. as well as ideal for cutting any residual internally generated noise from the latter stages of receivers using very narrow CW filters.

SPECIFICATIONS

Speaker Element :

Diameter 120 mm
Power Rating 3 watts
Impedance 8 ohms
Frequency Range 100-1200Hz

Filter Circuit Selections

LOW 1	below 300Hz	(-6db/octave)
2	below 600Hz	(-6db/octave)
HIGH 1	above 2.4kHz	(-6db/octave)
2	above 1kHz	(-6db/octave)
3	above 700Hz	(-6db/octave)

General :

Case Dimension (HWD) 129×200×306(mm)
Weight 2.2kg

YAESU MUSEN CO., LTD.
C.P.O. BOX 1500
TOKYO, JAPAN

