

ALINCO

Simple-Clean-Dependable

The World Awaits You.

Come Experience the Excitement of Shortwave Radio!



NEW

LW/MW/SW All Mode Desktop Communications Receiver

DX-R8T/E



Shown with optional accessories.



Now you can enjoy the thrill of listening to live radio signals from all over the world with the Alinco DX-R8T/E. A new desktop radio designed to be affordable without compromising performance, the DX-R8T/E boasts a communications grade receiver circuit, 3 ceramic filters (FM/AM, SSB, CW) with narrow filter function, excellent 1ppm stability and a large, easy-to-read LCD screen. The I/Q mode with supporting SDR freeware lets you output the I/Q signal from the 3.5mm stereo jack and decode DRM using only a PC and a sound card. Simple operating commands and straight-forward key layout make this a radio that you can start enjoying from the moment you first turn it on. Packed with many features normally found only in more expensive receivers, the DX-R8T/E is ready to capture the imagination of everyone from a beginner in the world of shortwave to the most experienced shortwave listener.

Attention : This product requires an optional power-supply (3A-class /12Vdc) and an external antenna to operate.

LW/MW/SW All Mode Desktop Communications Receiver

Features

- I/Q signal output allows use of third-party SDR software
- 150 kHz~35MHz (T-model up to 30MHz) in AM/USB/LSB/CW/FM and IQ modes
- Front and rear jacks make connecting accessories easy
- Direct frequency input to the dual VFO system
- Detachable front-control panel offers more mounting options
- Large LCD display makes operation simple
- Front-speaker and powerful 2W audio output makes it easy to hear signals
- Rugged, die-cast chassis
- Narrow ceramic filters (AM 2.4kHz/SSB 1kHz) and 0.5kHz audio-filtering for CW
- 4-level RF preamp/attenuator
- IF shift and RIT reduces interference
- Noise blanker enables clearer reception
- 3 banks/600 memory channels make it easy to save banks of favorite frequencies
- Two sets of programmed search pairs and varieties of scanning modes
- Auto-power-off, Sleep-timer, Dial and Key locks, RX indicator illumination and more!
- Computer utility software makes it easy to manage settings and edit memories
- Monitor shortwave signals from aviation, navigation and data sources



Free utility/SDR software is downloadable from <http://www.alinco.com>

Standard accessories

- Instruction manual
- EDC-37 DC cable

Standard accessories declared herein are our factory default and may vary at moment of sales depending on the market and Dealers' sales policy.



Optional accessories

Description	Cigar-Plug	DC cable	PC cable	Front control remote cable
Model	EDC-36	EDC-37	ERW-7	EDS-17
Remarks	Noise filter	(spare)	USB port	5m cable/bracket/panel

Specifications

Frequency range	T : 150KHz~29.99999MHz E : 150KHz~34.99999MHz	
Receiving mode	AM/FM/CW/USB/LSB/IQ	
Antenna impedance	50Ω unbalanced	
Ground method	Negative ground	
Frequency stability	±1ppm	
Dimensions (without projections)	240 (W) x 100 (H) x 293 (D) mm 9.45 (W) x 3.97 (H) x 11.54 (D) in	
Weight	4.1 kg (9 lbs)	
Operating temperature	-10°C to 60°C (+14°F to +140°F)	
Power requirements	13.8V DC ±15% (11.7 to 15.8V)	
Current drain	1A max	
Memories	200 channels × 3 banks = 600ch	
Receiver type	Double conversion superheterodyne	
Sensitivity	SSB	0.15 to 1.8MHz 0dBu(1uV)
	CW	1.8 to 30MHz -12dBu(0.25uV)
	AM	0.15 to 1.8MHz +20dBu(10uV)
		1.8 to 30MHz +6dBu(2uV)
FM	28 to 30MHz -6dBu(0.5uV)	
Intermediate frequency	1st 71.75MHz	2nd 455kHz
Selectivity	SSB, CW, AM (narrow)	2.4kHz/-6dB 4.5kHz/-60dB
	AM, FM	6kHz/-6dB 18kHz/-60dB
Spurious and image rejection ratio	More than 70dB	
Audio output power	More than 2.0W (8Ω,10%THD)	
RIT variable range	±1.2kHz	



7-digit alphanumeric channel tags make operation simple!

Authorized Dealer:

Copyright Alinco, Inc., Osaka, Japan. All rights reserved. Although Alinco has designed this brochure to be as accurate and comprehensive as possible, we reserve the right to make changes at any time to our equipment line, optional accessories, specifications, standard accessories, or availability of any such devices we manufacture and distribute. Please note that certain products and accessories may not be available in all countries of distribution therefore consult your Authorized Alinco Dealer for product availability and pricing. Colors of images herein may appear slightly different from actual products due to print. Projections are not included in the declared dimension values. Cellular frequencies can't be received.

RoHS E:

ALINCO, INC. Electronics Division

Yodoyabashi Dai-Bldg 13F, 4-4-9 Koraihashi,
Chuo-ku, Osaka 541-0043 Japan
Phone: 06-7636-2362 Fax: 06-6208-3802
<http://www.ALINCO.com>
E-mail: export@alinco.co.jp