

# M11 from TAD Radio



- **100 Channels**
- **Covers 138-174 MHz**
- **Shallow depth creates positioning options**
- **Manual Squelch control**
- **8ohm 5W front firing mylar speaker**
- **Loud in any environment**
- **Reliable microphone with up/down channel selector**



# M11

FM VHF MOBILE TRANSCEIVER

## SPECIFICATIONS

### General

Frequency Range	138 MHz ~ 174 MHz
Number of Channels	100 channels
Modulation	16K0F3E Wide 11K0F3E Narrow
Frequency Stability	± 5ppm
Operating Temperature Range	-30°C ~ 60°C
Power Supply Voltage	13.6V DC ± 15%
Antenna	50 ohms
Dimensions	W 180mm H 100mm D 85mm
Weight	1.2kg

### Transmitter

Output Power	30W
Max Deviation	± 5kHz

### Receiver

Intermediate Frequency	1st - 21.4 MHz 2nd - 455 kHz
Audio Output	3W type at 10% distortion with 8 ohms

### Others

Microphone Connector	1 GND (MIC), 2 PTT, 3 MIC, 4 GND, 5 HOOK, 6 +13.6V, 7 UP, 8 Down
User Operational Keys	Scan
Programming Method	PC
Memory System	EEProm
Tone System	CTCSS (50 tones)
DCS	83 Standard & Complimentary
Standard Accessories	Microphone, Mounting Bracket, Power Cable
Optional Accessories	MTS Board, DTMF Mic

**TAD RADIO of CANADA Inc**  
3663 Opie Cres. Prince George, BC V2N 1B9  
Phone: (866)564-5517 Fax: (250)563-2095  
Email: sales@tadradio.com www.tadradio.com

**TAD RADIO of CANADA Inc**  
P.O. Box 10160  
Spokane WA 99209  
Phone: (800)776-5817 Fax: (509)467-5031

LOCAL DEALER:

