

PNP-7DK INTERFACE CABLE

THIS CABLE IS TO INTERFACE THE IKENWOOD TS-930 TO THE AMERITRON ARB-704

PNP-7DK

1. Connect the 5 pin end of the Plug and Play cable to the multi-pin of the ARB.
2. Connect the 7 pin end of same cable to the Remote jack of the Kenwood.
3. Connect a Phono cable from amp of ARB to relay of amplifier.
4. If using ALC connect a Phono cable from ALC of ARB to ALC of amplifier.
5. Connect the power cord, that came with the ARB-704, to a 12Vdc power supply.
Connect Red lead to the positive (+) terminal of the power supply. Connect Black to ground, negative (-) or chassis of the power supply.
6. Connect the power plug to the power jack of the ARB.

The Radio jack on the ARB is not used in this application.

The Remote circuit on some Kenwoods have to be activated. Refer to the Kenwood's Owner manual.

When the transceiver is placed into transmit, the light on the ARB should illuminate and the Amplifier should go into transmit mode.