

RUSSIAN-EUROPEAN/AMERICAN TUBE EQUIVALENTS

SMALL SIGNAL DIODES

6X2П 6AL5, EAA91, EB91 =6X2P
6X6C 6H6 =6X2S

RECTIFIERS

5L3C 5U4G, GZ31 =5Z3S
5L4C 5Z4, GZ30 =5Z4S
6L5C 6X5GT, EZ35 =6Z5S

HIGH VOLTAGE RECTIFIERS

1L1C 1Z1 =1Z1S
1L7C 1AU3, DY30 =1Z7S
1L21П 1S2, DY86, DY87 =1Z27P

2L2C 2X2 =2Z2S
3L16C 3A3, 3B2 =3Z16S
3L22C GY501 =3Z22S

SUPPRESSOR DIODES

6L17C 6AU4GT =6Z17S
6L20П 6V3 =6D20P

TRIODES

2C4C 2A3 =2S4S
6C1П 9002 =6S1P
6C1Ж 955 =6S1SH
6C2C 6J5 =6S2S
6C2П EC98 =6S2P
6C4C 6B4G =6S4S
6C5C 6C5 =6S5S
6C20C 6BK4 =6S20S
6C51H 7586 =6S51N
6C52H 7895 =6S52N
6C53H EC1010 =6S53N
6Ф5C 6F5 =6F5S

COMBINATION DIODES/TRIODES

6Г1 6SR7 =6G1
6Г2 6SQ7 =6G2
6Г3П 6AK8, EABC80 =6G3P
6Г7 6Q7 =6G7
12Г1 12SR7 =12G1
12Г2 12SQ7 =12G2

DOUBLE TRIODES

6H3П 2C51, 6385 =6N3P
6H5C 6AS7G =6N5S
6H7C 6N7 =6N7S
6H8C 6SN7GT, ECC32 =6N8S

6H9C 6SL7GT =6N9S
6H10C 6SC7 =6N10S
6H13C 6080 =6N13S
6H14П 6CW7, ECC84 =6N14P
6H15П 6J6, ECC91 =6N15P
6H23П 6DJ8, ECC88 =6N23P
6H24П 6FC7, ECC89 =6N24P
6H27П 6GM8, ECC86 =6N27P
12H10C 12SC7 =12N10S
12H11C 12AH7GT =12N11S

SHARP CUTOFF PENTODES

6Ж1Ж 954 =6SH1SH
6Ж1П 6AK5, EF95 =6SH1P
6Ж2П 6AS6 =6SH2P
6Ж3 6SH7 =6SH3
6Ж3П 6AG5, EF96 =6SH3P
6Ж4 6AC7 =6SH4
6Ж4П 6AU6, EF94 =6SH4P
6Ж5П 6AH6 =6SH5P
6Ж6C Z62 =6SH6S
6Ж7 6J7 =6SH7
6Ж8 6SJ7 =6SH8
6Ж9П E 180 F, 6688 =6SH9P
6Ж15П 6EJ7, EF184 =6SH15P
6Ж32П EF86, 6267 =6SH32P
6Ж40П 6ET6, EF98 =6SH40P
6Ж51П 6EJ7, EF184 =6SH51P
12Ж8 12SJ7 =12SH8

REMOTE CUTOFF PENTODES

1K1П DF961 =1K1P
1K2П 1F34 =1K2P
6K1П 9003 =6K1P
6K1Ж 956 =6K1SH
6K3 6SK7 =6K3
6K4 6SG7 =6K4
6K4П 6BA6, EF93 =6K4P
6K7 6K7 =6K7
6K8П 6ES6, EF97 =6K8P
6K13П 6BY7, EF85 =6K13P
12K3 12SK7 =12K3
12K4 12SG7 =12K4

POWER TETRODES AND PENTODES

2П1П 2L32 =2P1P

2П2П 2L34 =2P2P
6П3C 6L6 =6P3S
6П6C 6V6 =6P6S
6П7C 6BG6G =6P7S
6П9 6AG7 =6P9
6П14П 6BQ5, EL84 =6P14P
6П18П 6DY5, EL82 =6P18P
6П20C 6CB5 =6P20S
6П27C 6CA7, EL34 =6P27S
6П31C 6CM5, EL36 =6P31S
6П33П 6CW5, EL86 =6P33P
6П36C 6GB5, EL500 =6P36S
6Ф6C 6F6G =6F6S
Г-807 807 =G-807

COMBINATION DIODES AND PENTODES

1Б2П 1AF34 =1B2P
6Б8 6B8 =6B8

COMBINATION TRIODES AND PENTODES

6Ф1П 6BL8, ECF80 =6F1P
6Ф3П 6BM8, ECL82 =6F3P
6Ф4П 6DX8, ECL84 =6F4P
6Ф5П 6GV8, ECL85 =6F5P
9Ф8П 9A8, PCF80 =9F8P
15Ф4П 15DX8, PCL84 =15F4P
16Ф3П 16A8, PCL82 =16F3P
18Ф5П 18GV8, PCL85 =18F5P

MULTIPLE GRID TUBES

1A2П 1H34 =1A2P
6A2П 6BE5, EK90 =6A2P
6A3П 6BN6 =6A3P
6A7 6SA7 =6A7
6A8 6A8 =6A8
6A10C 6SA7 =6A10S
6Л7 6L7 =6L7

COMBINATION TRIODES/MULTIPLE GRID TUBES

6И1П 6AJ8, ECH81 =6И1P
6И4П 6V9, ECH200 =6И4P

DISPLAY TUBES

6E1П 6BR5, EM80 =6E1P