

5/1/69

HEATHKIT TUBE DATA SERVICE  
P. O. BOX 377  
HEWLETT, L. I., N. Y. 11557

MODEL TT-1/A  
NEW TUBE RELEASES  
for use with  
1-1-69 ROLL CHART

TUBE	PLATE	BIAS	FIL.	METER	SIG.	SELECTORS	R. P.	REMARKS
1DK29	E	-	1.5	42	D	76000-0000-000	-	Di; insert 2 base leads into pins 1&2 of 9 pin min. socket. Use plate cap on single lead;F
3M-P26	C	25H	600	37	2	51763-4000-000	1300	Pe
4M-P26	C	25H	450	37	2	51763-4000-000	1300	Pe
4R-HH2	C	10L	600	37	4	35176-PGK0-000	1170	Tr.#1&#2;K1, P1, G1&K2, P2, G2
5M-HH3	C	10L	600	39	4	3P76G-5100-000	1007	Tr.#1&#2 P1, G1 &P2, G2
5MK9	E	-	600	25	R	00763-0000-000	-	
5R-K16	B	-	5	19	R	P0076-0030-000	-	F; P1 & P2
6AJ9*	C	10L	450	35	4	10007-6003-000	1100	Decal;*Grid cap.Tr.
"	D	14L	450	21	8	01527-6340-000	1050	Decal;*Pe;X7
6BD7	F	OL	6.3	32	1	35176-0000-000	1300	Tr.
"	B	-	6.3	31	D	00176-30P0-000	-	Di#1&#2, P1 & P2
6CH6	C	27L	6.3	44	2	05176-0342-000	1300	Pe
6DS8	O	10L	300	45	1	45176-3300-000	1350	Hep
"	O	OL	300	47	1	00176-0035-000	1380	Tr
6ES6	O	17L	300	20	1	51763-4200-000	1300	Pe
6ET6	O	25L	300	20	1	51763-4200-000	1300	Pe
6G-B3	C	20H	6.3	26	4	07045-0610-000	1235	Pe;plate cap; X7
6G-B6	D	30H	6.3	33	4	07045-0610-000	1082	Plate cap; X3
6G-K17	E	-	6.3	25	R	00103-0760-000	-	
6GS7	D	12L	6.3	33	8	00076-3415-000	1100	Pe;X6
"	C	30L	6.3	27	2	53176-0000-000	1100	Tr; X3
6M-HH3	C	10L	450	39	4	3P76G-5100-000	1007	Tr #1&#2 P1, G1&P2, G2
6N3	E	-	6.3	25	R	00176-0003-000	-	
6R-HH2	C	10L	6.3	37	4	35176-PGK0-000	1170	Tr#1&#2;K1 P1 G1 & K2, P2, G2
6R-K19	E	-	6.3	25	R	10076-0003-000	-	Connect aux. lead from pin #1 of octal socket to cath. cap
6R-P15	F	20H	6.3	32	4	G5176-0304-000	1250	Pe;G1 & G2
6U3	B	-	6.3	20	R	00176-0003-000	-	Rect
7AN7	C	10L	300	36	4	15376-G0KP-000	1300	Tr#1&#2 K1, P1, G1 &K2, P2, G2
7ES8	C	14L	300	29	8	PGK76-3510-000	810	K1, P1, G1&K2, P2, G2, X10
7M-P18	F	27H	7.5	27	2	G1763-4500-000	1300	Pe;G1&G2
8KR8	D	25L	7.5	28	8	00076-1543-000	1300	Pe;X10
"	C	10L	7.5	34	4	15376-0000-000	1250	Pe; X5
9M-HH3	C	10L	10	39	4	3P76G-5100-000	1007	Tr#1&#2 P1, G1 & P2, G2
9M-P12	D	OL	10	33	4	51763-4000-000	1100	Pe; X3
11AF9*	D	26L	10	34	8	00007-6154-000	1150	Decal*;plate cap Pe#1
"	D	21L	10	33	4	51437-6000-000	1100	Decal*; Pe#2

(OVER)

TUBE	PLATE	BIAS	FIL.	METER	SIG.	SELECTORS	R. P.	REMARKS
12G-B7	D	30H	13	33	4	07045-0610-000	1190	Plate cap
17LD8	D	25H	450	31	4	05176-3400-000	1000	Pe; X5
"	F	23H	450	40	1	10076-0035-000	1462	Tr; X1
18R-AL1	F	27H	13	41	1	00076-3510-000	1300	Tr#1; X1
"	O	OL	13	23	2	3G576-0001-000	1100	Tr#2 G1&G2, X3
19MR9	C	10L	20	16	1	52763-4100-000	1100	Pe
19X3	B	-	20	20	R	00176-0003-000	-	Rect
25B-B14*	C	18H	300	40	8	G5K76-4010-000	1100	*Magnoval Pe;plate cap K1&K2 G1&G2
38A3	B	-	35	20	R	00176-0003-000	-	Rect
8417	F	30H	6.3	5	2	07345-0610-000	1200	Pe; X11