



VALVES	1	2	3	4	5	6	7	8
V1,3,4,6.	H	A	AD	G3	G2	G1	KS	H
V2.	H	AH	AT	G3	G2	G1	K	H
V5	H	A	K	G3	G2	G1	K	H
V7	H	A	-	-	-	-	K	H

### EDDYSTONE "840A" COMPONENT VALUES

#### CONDENSERS.

C1 ...	1800 pf.	H.V. Ceramic.
C2 ...	1800 pf.	H.V. Ceramic.
C3 ...	·01 mfd.	Tub. Paper A.C.Wkg.
C4 ...	3-23 pf.	Air Trimmer.
C5 ...	10 pf.	Silvered Mica.
C6 ...	3-23 pf.	Air Trimmer.
C7 ...	6 pf.	Silvered Mica.
C8 ...	3-23 pf.	Air Trimmer.
C9 ...	2-23 pf.	Air Trimmer.
C10 ...	11-5-366 pf.	R.F. Section 3 Gang.
C11 ...	100 pf.	Silvered Mica.
C12 ...	·1 mfd.	Tub. Paper.
C13 ...	·1 mfd.	Tub. Paper.
C14 ...	20 pf.	Silvered Mica.
C15 ...	3-23 pf.	Air Trimmer.
C16 ...	6 pf.	Silvered Mica.
C17 ...	3-23 pf.	Air Trimmer.
C18 ...	3-23 pf.	Air Trimmer.
C19 ...	3-23 pf.	Air Trimmer.
C20 ...	11-5-366 pf.	F.C. Section 3 Gang.
C21 ...	·1 mfd.	Tub. Paper.
C22 ...	·1 mfd.	Tub. Paper.
C23 ...	·0005 mfd.	Moulded Mica.
C24 ...	100 pf.	Ceramic.
C25 ...	3-23 pf.	Air Trimmer.
C26 ...	3-23 pf.	Air Trimmer.
C27 ...	3625 pf.	Silvered Mica. ±1%.
C28 ...	2825 pf.	Silvered Mica. ±1%.
C29 ...	1040 pf.	Silvered Mica. ±1%.
C30 ...	3-23 pf.	Air Trimmer.
C31 ...	400 pf.	Silvered Mica. ±1%.
C32 ...	3-23 pf.	Air Trimmer.
C33 ...	11-5-366 pf.	Osc. Section 3 Gang.
C34 ...	3 pf.	Silvered Mica.
C35 ...	·01 mfd.	Tub. Paper.
C36 ...	100 pf.	Silvered Mica.
C37 ...	100 pf.	Silvered Mica.
C38 ...	100 pf.	Ceramic.
C39 ...	100 pf.	Silvered Mica.
C40 ...	100 pf.	Silvered Mica.
C41 ...	·1 mfd.	Tub. Paper.
C42 ...	50 mfd.	Tub. elect.
C43 ...	·01 mfd.	Moulded Mica.
C44 ...	·01 mfd.	Tub. Paper.
C45 ...	·1 mfd.	Tub. Paper.
C46 ...	·1 mfd.	Tub. Paper.
C47 ...	·1 mfd.	Tub. Paper.
C48 ...	20 pf.	Silvered Mica.
C49 ...	100 pf.	Silvered Mica.
C50 ...	100 pf.	Silvered Mica.
C51 ...	30 mfd.	Elect. at 15v. DC.
C52 ...	·1 mfd.	Tub. Paper.
C53 ...	30 mfd.	Elect. at 15v. DC.
C54 ...	100 pf.	Silvered Mica.
C55 ...	100 pf.	Silvered Mica.
C56 ...	100 pf.	Silvered Mica.
C57 ...	·01 mfd.	Tub. Paper.
C58 ...	·01 mfd.	Tub. Paper.
C59 ...	·01 mfd.	Tub. Paper.
C60 ...	·01 mfd.	Moulded Mica.
C61 ...	·01 mfd.	Tub. Paper AC. Wkg.
C62 ...	50 mfd.	Elect. 450v. D.C
C63 ...	50 mfd.	Elect. 450v. DC.
C64 ...	·01 mfd.	Tub. Paper.
C65 ...	3 pf.	Silvered Mica.
C66 ...	·01 mfd.	Moulded Mica.
C67 ...	·0005 mfd.	Moulded Mica.

#### RESISTORS

R1 ...	47,000 ohms.
R2 ...	22,000 ohms.
R3 ...	10,000 ohms.
R4 ...	47,000 ohms.
R5 ...	0·73 megohm.
R6 ...	22,000 ohms.
R7 ...	0·2 megohm.
R8 ...	0·1 megohm. 1W.
R9 ...	0·47 megohm.
R10 ...	330 ohms. (5%)
R11 ...	3,300 ohms.
R12 ...	0·47 megohm.
R13 ...	47,000 ohms.
R14 ...	220 ohms.
R15 ...	22,000 ohms.
R16 ...	22 ohms.
R17 ...	47 ohms.
R18 ...	560 ohms.
R19 ...	0·47 megohm.
R20 ...	330 ohms. (5%)
R21 ...	0·47 megohm.
R22 ...	2·0 megohm.
R23 ...	1·0 megohm.
R24 ...	0·1 megohm.
R25 ...	0·1 megohm.
R26 ...	2,700 ohms.
R27 ...	50,000 ohms. Potentiometer.
R28 ...	0·47 megohm.
R29 ...	150 ohms.
R30 ...	10,000 ohms.
R31 ...	47,000 ohms.
R32 ...	47,000 ohms.
R33 ...	0·27 megohm.
R34 ...	10,000 ohms. Potentiometer.
R35 ...	0·5 megohm. Potentiometer
R36 ...	500 ohms. 3 amp. with 3 Variable Taps.
R37 ...	Thermistor.
R38 ...	1,000 ohms.
R39 ...	2·0 megohms.
R40 ...	2·2 megohms.
R41 ...	50 ohms. (W.V. 6 watt)

Fixed resistors are 1/2 watt except where otherwise stated.